

Porting Process DE

**Porting Guidance for Customer
On how to fill
DE GNP Porting Letter of Authority (LOA)**

Process Description-

We have a copy of standard porting LOA for porting geographic numbers (GNP) as following for a walkthrough with details-

Anbieterwechsellauftrag von Wildix OÜ

tick if the service is still active at the losing provider or if the contract was ceased but the contract termination date is in the future

Kündigung von Anschlüssen beim Endkundenvertragspartner abgebend (EKPaBg)
(separate Kündigung beim bisherigen Anbieter nicht erforderlich)
 Hiermit kündige/n ich/wir den zu unten gemachten Angaben gehörenden Anschluss bei:
 zum nächst möglichen Termin. (name of the losing provider/

Hiermit beauftrage/n ich/wir die Portierung (Mitnahme) der angegebenen Rufnummer/n.

Name/Firma : ABC GmbH (Company Name) Vorname: _____
 Straße: ABC-Strasse (Street name) Hausnr.: 3 (building number)
 PLZ: 12345 (postal code) Ort: Berlin (city/location) Site address required matching the local area code

Ortsnetz-kennzahl	Rufnummer/n <small>(add up to 10 single numbers, only if they belong to the same service connection) (Achtung, es muss mindestens eine Rufnummer angeben werden!)</small>		
<input checked="" type="checkbox"/> alle Nr. der Anschlüsse portieren	<u>030</u> (local area code)	<u>123400</u>	<u>123401</u>
		<u>123403</u>	<u>123405</u>
	<u>123406</u>	<u>123407</u>	<u>123411</u>
			<u>123432</u>

mark only if cust. wants to port
 all numbers from the contract/access line

Telekommunikations-
 anlagen: 1234 Durchwahl-RN - Abfragestelle Rufnummernblock:
 number with range: (main number) - 0 von 00 (range start) bis 99 (range end)
(switchboard number - is the same as the first digit from the range start - Rufnummernblock von -

ATTENTION!! single numbers have to be requested separately from numbers with ranges,
 a separate porting form is required for each number with range

Ort, Datum: Musterhausen, 13.02.2013 Unterschrift: _____
 (location, date)

(signature and company stamp
 - both mandatory for companies)

Vertragspartner und ggf. Firmenstempel

ATTENTION!! single numbers have to be requested separately from numbers with ranges,
 a separate porting form is required for each number with range

(signature and company stamp
 - both mandatory for companies)

Ort, Datum: Musterhausen, 13.02.2013
 (location, date)

Unterschrift: _____

Vertragspartner und ggf. Firmenstempel

von den beteiligten Endkundenvertragspartnern (EKP) auszufüllen	WBCI-GF: <input type="text"/>	Vorab-ID: _____	Änderungs- / Storno-ID _____	
	PKlauf: _____	Wechselermin: _____	neuer Wechselermin: _____	
	Portierungsfenster: <input checked="" type="checkbox"/> 06:00 - 8:00 Uhr	<input type="checkbox"/> 06:00 - 12:00 Uhr	<input type="checkbox"/> _____	
	Rückinformation an: _____	über Fax/E-Mail: _____	Tel.: _____	
	Ressourcenübernahme: <input type="checkbox"/> ja <input checked="" type="checkbox"/> nein	Sicherer Hafen: <input type="checkbox"/>	Storno ausgeführt: <input type="checkbox"/> ja <input type="checkbox"/> nein	
	Zustimmung: ZWA <input type="checkbox"/> NAT <input type="checkbox"/> ADA <input type="checkbox"/>	Datum: _____	Ist-Technologie: _____	
	WITA: <input type="checkbox"/> S/PRI: <input type="checkbox"/>	WITA-Vertragsnummer / Line-ID: _____		
	Grund: _____			
	Ablehnung: ADF <input type="checkbox"/> KNI <input type="checkbox"/> VAE <input type="checkbox"/> RNG <input type="checkbox"/> WAI <input type="checkbox"/> AIF <input type="checkbox"/> SON <input type="checkbox"/>			
	Ortsnetzkenzahl _____			
Rufnummer/n	PKI abg	PKI abg	Bei Telekommunikationsanlagen:	
_____ - _____	_____	_____	Durchwahl-RN - Abfragestelle _____	
_____ - _____	_____	_____	_____ - _____	
_____ - _____	_____	_____	Rufnummernblock _____	
_____ - _____	_____	_____	von _____ bis _____	
_____ - _____	_____	_____	PKI abg _____	
Ansprechpartner _____	über Fax/E-Mail: _____	Tel.: _____		
interne Bemerkungen				

ENGLISH TRANSLATION FOR CONVENIENCE PURPOSES

Porting order from

Wildix OÜ

Please terminate the service connection/access line at the losing provider (EKPaag)

(separate cease order at the current provider not required). With this I am asking to terminate the below mentioned access line at the losing provider:

With this I am requesting the porting of the below mentioned number/numbers.

(customer name and first name if residential)

Company / Surname: _____

First name: _____

Street name: _____

Building nr: _____

PLZ : (postal code) _____ City: _____

ATTENTION address must match the local area code

Port all single nr. from the access line

Local area code

single numbers

Add up to 10 single numbers, only if they belong to the same service connection. Attention, at least one single number of the service connection to be mentioned!

_____	_____	_____
_____	_____	_____
_____	_____	_____

Number with range as type:

Main number: _____

Switchboard nr. _____

Range start _____

Range end _____

(switchboard number)

- is the same as the first digit from the range start

TENTION!! Do not enter single numbers and ranges on the same form
a separate porting form is required for each number with range
a separate form for single numbers

Location, Date: _____

Unterschrift: _____

(signature and stamp both required for companies
- For residential only signature is required)

WBCI-GF: <input type="text"/>	Vorab-ID: _____	Änderungs- / Storno-ID _____
PKlauf: _____	Wechseltermin: _____	neuer Wechseltermin: _____
Portierungsfenster: <input type="checkbox"/> 06:00 - 8:00 Uhr <input type="checkbox"/> 06:00 - 12:00 Uhr <input type="checkbox"/> _____		
Rückinformation an: _____	über Fax/E-Mail: _____	Tel.: _____

- Please terminate the service connection/access line at the losing provider (EKPaag)** – If you do not mark this box porting without contract termination "Kündigung von Anschlüssen ..." is only possible for number with ranges if the contract was terminated and the cease date is in the past. As long the contract is still active at the losing provider or terminated with a future cease date, porting incl. contract termination should be requested (tick the box: Kündigung von Anschlüssen...)
- With this I am requesting the porting of the below mentioned number/numbers-** This always has to be marked

According to the German regulatory rules:

A range is defined as a multiple of 10 or 100 or 1000 or 10000 numbers, the multiplier by definition smaller or equal to 10.

This means 10, 20, 300, 500, 3000 is fine, 1200 is wrong.

The last digit of the **range start must be '0'**, the last digit of the **range end must be '9'**.

We are not allowed to port a part of a number range or to split a range in more ranges; according the regulatory rules in Germany we are only allowed to port full number range as they were originally assigned

A number is formed of maximum 11 digits including the digits of the range and without counting the leading Zero of the local area code.

There are some exceptions for single numbers that can't be ported because they are too long, technically not portable.

Exception for single numbers in Berlin, Frankfurt, Munchen, Hamburg:

If we have a local area code of 3 digits (030) the complete number, without counting the leading 0 should be formed of:

· *max. 10 digits for single numbers (with a local area code of 3 digits 030, 069, 089, 040...) ex 030 12345678 (030 123456789 would be too long, 11 digits)*

· *max. 11 digits for numbers with number ranges (030 123456780 – 123456789 would be ok 11 - digits)*

Note: Please keep a copy of latest invoice handy while filling out the LOA with following inputs required.

FOR INTERNAL SYSTEM RECORDS The switchboard number (Switchboard nr. / Abfragestelle) is the same with the first digit of the range start (Runnummernblock von)
